



## ROUGHNECK STANDBY GASEOUS: 125KW

The **WILDCAT ROUGHNECK** 125KW emergency standby stationary gaseous generator is commercial grade and designed to run for extended periods of time as needed.

### Durable Industrial Engine

Usually reserved for industrial applications, the power plant is a premier industrial fixed speed (1,800 RPM) engine built to provide strong, reliable power without giving up quiet operation and engine longevity.

### Digital Controls

Designed for single genset applications, the digital controls monitor the genset's voltage, current, power, frequency, engine speed, oil pressure and coolant temperature on a back-lit LCD display for ease of use.

### Quality Clean Power

Voltage regulation ensures that electronics are safely powered with less 5% total harmonic distortion (THD) at no load.

### Industrial Class Alternator

Protected with Class H insulation and standard 40° C nominal rating, the standard 12-wire winding and 2/3 pitch meet all key international standards and regulations.

### NFPA-110

Genset is designed to exceed NFPA-110, Level 2 Emergency Power Supply Systems (EPSS) by providing prime power (PP) to meet EPSS Class 168 Type 10.

### Easy To Service

Preventative maintenance and in-field repairs are made easier with our simplified engineering and non-proprietary parts.



### Engine Make & Model

Origin Engines OE62L125TC

### Alternator Make & Model

Stamford UCI274E

### Controller Make & Model

Deep Sea Electronics 6110

### Assembled Weight (lb / kg)

8,000 lbs 3,629 kgs

### Overall Dimensions (in / mm)

148L x 59W x 79H 3759L x 1499W x 2007H

## GENERATOR SET RATINGS

| Model                                      | Voltage                             | Power Factor | Phase | Hertz | Circuit Breaker Amps | KW  | KVA | BHP | Duty Cycle                   | Certifications        |
|--------------------------------------------|-------------------------------------|--------------|-------|-------|----------------------|-----|-----|-----|------------------------------|-----------------------|
| <b>Roughneck</b><br>NG 125<br>RO0125NGA*XE | 120 / 240                           | 1.0          | 1     | 60    | 450                  | 90  | 90  | 204 | Emergency Standby Stationary | EPA Emergency Standby |
| <b>Roughneck</b><br>LP 125<br>RO0125PLA*XE | 120 / 240                           | 1.0          | 1     | 60    | 450                  | 90  | 90  | 175 | Emergency Standby Stationary | EPA Emergency Standby |
| <b>Roughneck</b><br>NG 125<br>RO0125NG**XE | 208 / 120<br>240 / 120<br>480 / 277 | 0.8          | 3     | 60    | 450<br>450<br>200    | 125 | 156 | 204 | Emergency Standby Stationary | EPA Emergency Standby |
| <b>Roughneck</b><br>LP 125<br>RO0125PL**XE | 208 / 120<br>240 / 120<br>480 / 277 | 0.8          | 3     | 60    | 450<br>450<br>200    | 100 | 125 | 175 | Emergency Standby Stationary | EPA Emergency Standby |

Confidential and proprietary - all rights reserved. © 2025 Engines LPG, LLC dba WILDCAT PowerGen. Use or duplication is expressly prohibited without the express consent of WILDCAT Power Gen.