



ROUGHNECK STANDBY GASEOUS: 200KW

The **WILDCAT ROUGHNECK** 200KW emergency standby stationary gaseous generator is commercial grade and designed to run for extended periods of time as needed.

Durable Industrial Engine

Usually reserved for industrial applications, the power plant is a premier industrial fixed speed (1,800 RPM) engine built to provide strong, reliable power without giving up quiet operation and engine longevity.

Digital Controls

Designed for single genset applications, the digital controls monitor the genset's voltage, current, power, frequency, engine speed, oil pressure and coolant temperature on a back-lit LCD display for ease of use.

Quality Clean Power

Voltage regulation ensures that electronics are safely powered with less 5% total harmonic distortion (THD) at no load.

Industrial Class Alternator

Protected with Class H insulation and standard 40° C nominal rating, the standard 12-wire winding and 2/3 pitch meet all key international standards and regulations.

NFPA-110

Genset is designed to exceed NFPA-110, Level 2 Emergency Power Supply Systems (EPSS) by providing prime power (PP) to meet EPSS Class 168 Type 10.

Easy To Service

Preventative maintenance and in-field repairs are made easier with our simplified engineering and non-proprietary parts.



Engine Make & Model

Origin Engines OE103L200TC

Alternator Make & Model

Stamford UCI274G

Controller Make & Model

Deep Sea Electronics 6110

Assembled Weight (lb / kg)

12,500 lbs 5,670 kgs

Overall Dimensions (in / mm)

200L x 80W x 100H 5080L x 2032W x 2540H

GENERATOR SET RATINGS

Model	Voltage	Power Factor	Phase	Hertz	Circuit Breaker Amps	KW	KVA	BHP	Duty Cycle	Certifications
Roughneck NG 200 RO0200NGA*XE	120 / 240	1.0	1	60	2100	160	200	298	Emergency Standby Stationary	EPA Emergency Standby
Roughneck LP 200 RO0200PLA*XE	120 / 240	1.0	1	60	2100	160	200	298	Emergency Standby Stationary	EPA Emergency Standby
Roughneck NG 200 RO0200NG**XE	208 / 120 240 / 120 480 / 277	0.8	3	60	900 800 400	200	250	298	Emergency Standby Stationary	EPA Emergency Standby
Roughneck LP 200 RO0200PL**XE	208 / 120 240 / 120 480 / 277	0.8	3	60	900 800 400	200	250	298	Emergency Standby Stationary	EPA Emergency Standby

Confidential and proprietary - all rights reserved. © 2025 Engines LPG, LLC dba WILDCAT PowerGen. Use or duplication is expressly prohibited without the express consent of WILDCAT Power Gen.